

# Compact

## Safety, power, durability



### User guide

The button:

Press and release: On/Off.

Press and hold down when the flashlight is turned **off**: Strobe.

Press and hold down when the flashlight is turned **on**: Continuous dimming control (loop).

Press the button 4 times within 2 seconds: The taillight turns orange, then press the button again within 2 seconds (while the taillight is orange), and the flashlight goes into SOS mode.

Press the button 4 times within 2 seconds: The taillight turns orange. After 2 seconds the taillight turns blue, then press the button again within 2 seconds (while the taillight is blue) and the flashlight button is locked (use this function when traveling by plane or whenever you want to prevent the flashlight from turning on accidentally). To unlock the button, press again 4 times within 2 seconds.

When you run your flashlight at maximum power for a long period of time under extremely hot conditions, it will automatically return to continuous drive mode. This prevents the flashlight from overheating, and ensures optimal battery life time.

### Taillight battery status indication

80-100%: 2 blue flashes  
60-80%: 4 blue flashes

40-60%: 2 orange flashes  
20-40%: 4 orange flashes  
0-20%: continuous orange light

### Maintenance

Cleaning: Just wash it under running water or with a dry cloth – no chemicals needed or advised. Storing: Keep your Wiseled flashlight within reach and charged – you never know when you will need it. Refurbishing: If the front- or backend of the flashlight wears out over the years, you can order new backend and frontend pieces.

### Charging

It's advised to always keep the flashlight fully charged.

Charging indicator cradle: Orange when charging  
Blue when 90% recharged

Charging time: 1 hour

You can either charge the flashlight in the charger cradle, or directly connect it to the cable. When you use a cradle, slide in the flashlight with the front facing directly towards you. When you use the charger cable directly, align the red dot on the cable with the marker on the flashlight.

WiseLED flashlights have to be kept fully charged at all times. Our warranty won't cover flashlights that have been left uncharged for a period of 2-3 weeks and this is not to happen more than 3 times, as this will significantly deteriorate the battery. The Li-ion batteries chemistry is not able to survive longer periods without energy so if not charged with a timely interval your batteries will get less efficient and the chemistry inside will eventually give up. So therefore remember always to fully recharge your flashlight before storing it for longer periods of time.



### Specifications

- 3 LED Efficiency 850 Lumen
- LED lifetime + 50,000 hours
- Battery: Rechargeable Li-ion
- Battery capacity: 7,4 volt 2.6 amps
- Light output duration:
  - 100%: 1 hours 45 min
  - 80%: 2 hours 30 min
  - 60%: 3 hours 30 min
  - 40%: 5 hours
  - 20%: 20 hours
- Dimmable: 5 steps
- Submersible: 300 feet
- Lens: 5 degree
- Anodized Aerospace grade aluminium
- Grip: Thermo plastic rubber
- Strobe effect: 200 watt (non-lethal weapon)
- Usable light: Range min. 600 feet (1 lux)
- Signalling: 4 miles in clear weather
- Weight: 415 grams / 14.6 oz
- Body diameter: 44 mm / 1.7"
- Overall length: 20.5 cm / 8"
- Build in taillight
- Battery indicator
- Build in antitheft chassis number
- Self-discharge time: 2.5 years

### CAUTION:

To extend battery lifetime adjust the power of the flashlight to your needs. When used with 100% power DO NOT leave unattended and use it (user serves as cooling device).

Don't use the backend of the Compact model for anything but charging.

### WARRANTY:

Guarantee conditions: You have a 2 year guarantee (limited guarantee for the batteries) if any problems arise with your WiseLED product. Return your WiseLED product to our address after which we will correct the problem as soon as possible or alternatively send you a new product. Vandalism, misuse or the like are not covered by the exchange rights. Enclose your receipt when exchanging the product. The warranty will become null and void if the product is misused, abused, tampered with or taken apart.



Visit [wiseled.com](http://wiseled.com) for more information